
# LAMINEX® PARTITIONING SYSTEMS SMF - SKIRT MOUNTED, FREESTANDING






Position saddles under the channel markings.

With a level, find the lowest saddle which is 172mm (standard) or otherwise nominated on the plans.

Level all other saddles down from the lowest saddle so as the nominated saddle height is highest saddle.




Fix channel "A" to back wall by placing on top of the leveled saddles.

#### DO NOT CUT

Level across from the top of channel "A" to wall markings for wall channel "B". This will give the starting point.

Holding the channel to the correct level measure up from the floor 122mm and mark wall channel "B".


This will give you the cut and installation size. Fit to wall.



### STEP 4

Draw a chalk line level with the inside edge of wall channel "B" to an equal distance from the opposite end.

This mark will give you the back edge of the floor mounts.



Place end nib into channel and level.


Mark floor to get measurement for end floor mount.

Cut floor mount Imm longer.

Cut the floor mount on end butting into the wall.


Fit floor mount to floor as per 'Fixing the Floor Mount System.'

Fit the end nib to the channel and floor mount.



## STEP 6

Place door spacers and floor mounts into position to check the overall dimensions.




Locate all divisional panels into the rear channels "A" resting onto the saddles.

#### DO NOT SCREW OFF YET

Fit the floor mount for the corresponding frontal hard against the door spacer.

Ensure that the back is level with the chalk line.



## STEP 8

Fit door hardware and hinges to door and nib. Fit wall channel "A" to the back of the frontal into the pre-drilled holes. Hang the door onto the end nib.


Place frontal over the division into position. The top height of the levelled division will give you the height of the frontal.

Measure from the floor to the height of the division, deduct 10mm for the cutting measurement of the frontal. Material can be cut using a jigsaw. Ensure that any deduction is made to the bottom of the panel.

Close the door and use 3mm packers between the frontal and door. Door frontal and division should be aligned.


Fit frontal as per 'Fixing the Floor Mount System.'

Repeat for additional doors.




When all cubicles have been assembled, place a string line across the fronts at the top of the cubicles.


Once all the fronts are lined up, divisions and end panels can be screwed off from the channels.



Apply silicon to the raised tongues and to the back of the end caps and gently tap into position.




# FIXING THE FLOOR MOUNT SYSTEM




#### Step I

Position the backing plate and mark holes.
Drill into the floor with the supplied masonary bit. Fit orange plugs into the holes.
Apply silicon to underside of the floor mount and fix with coach screws supplied.



#### Step 2

Fit and scribe the bottom of nibs and frontals to the required site level. (Height-10mm) This will keep the cut edge concealed in the floor mount.



#### Step 3

Fit the front plate onto the back plate. Fit board into position and level. Clamp Floor mount to sandwich the board firm. With the 8.5mm bit, drill the board through the selected holes provided in the aluminium. Hold nut inside the front plate and screw fix together.

# Also available in the Laminex® partitioning range:





















For more inspiration join us on facebook.com/thelaminexgroupau

For a sample call 1800 002 204. For more information visit laminex.com.au or call 132 136